

High Efficiency Redundancy Architecture in SRAM Compiler

Background of the Invention

Field of the Invention

[0001] This invention relates generally to integrated circuits and more particularly to yield enhancement circuits by implementing redundant sub-circuits for faulty sub-circuits of the integrated circuits. Even more particularly this invention relates to yield enhancement circuits for substituting redundant columns of memory cells for faulty columns of memory cells in memory arrays such as static random access memory (SRAM).

Description of Related Art

[0002] Yield enhancement circuitry for integrated circuits, particularly for memory integrated circuits, is well known in the art. Memory integrated circuits are formed of multiple arrays of memory cells. Each memory array is constructed of rows and columns of memory cells. Normally, the rows of memory cells are selected by an address decoder. The columns of memory cells are bounded by read/write buffers that retrieve data from and store data to the selected memory cell. A column decoder provides a selection mechanism to guide data from a selected column to the read/write buffers. The output of the read/write buffer is transferred to an input/output driver and receiver to transfer the data between the memory cells and external circuitry.

[0003] In the processing of the memory circuits, contamination or defects within the process will cause faults within the memory circuit. To compensate for the faults within the memory circuits, redundant rows and columns of memory cells are appended adjacent to the array or within the array of memory cells. In array organizations where multiple columns of memory cells are arranged to provide data for one input/output circuit, a redundant column may be placed adjacent to the columns and connected for implementation to only those columns associated with the input/output circuit. This organization places a large overhead in space for the redundancy. For instance if the input/output circuit has eight columns for containing the data and one column of redundancy, the overhead for the redundancy becomes approximately 12.5%.

[0004] As process techniques have improved, contamination and defects have decreased, thus ameliorating the need for such high levels of redundancy. Rather than having one redundant column of memory cells per input/output circuit, one redundant column is added, associated, or appended to an array of memory cells. In some cases, there may be one redundant column of memory cells for multiple arrays positioned on a substrate. The wiring to connect the redundant column of memory cells so that it can be connected within the array or arrays is relatively long and affects the performance of the memory.

[0005] Refer now to Fig. 1 for a description of a memory having a redundant column of memory cells associated with an input/output circuit. In this illustration the memory is constructed of two arrays of memory cells **5** and **10**. Within the

two memory arrays **5** and **10**, sub-arrays **15a**, **15b**, ..., **15z** and **20a**, ..., **20z** are composed of columns **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z**. A redundant column **35** of memory cells **40a**, **40b**, ..., **40z** is positioned to be associated with the columns **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z**.

5 Each of the columns **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z** is connected to one of the redundancy implementation switches **45a**, ..., **45z**. The redundant column **35** of memory cells **40a**, **40b**, ..., **40z** is connected to all the redundancy implementation switches **45a**, ..., **45z**.

[0006] The redundancy implementation switches **45a**, ..., **45z** are connected to
10 the fuse box **50** which provides the necessary programming or indication of a fault within the columns **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z**. If no fault occurs, the columns **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z** are connected directly to the read/write buffer **55**. However, if a fault is detected during testing of the memory, the fuse box **50** is programmed to indicate the
15 column **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z** containing the fault. The programming of the fuse box **55** sets the appropriate redundancy implementation switch **45a**, ..., **45z** associated with the faulty column **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z** such that the redundant column **35** of memory cells **40a**, **40b**, ..., **40z** is now connected to the read/write buffer **55**.

20 [0007] The read/write buffer **55** contains the necessary circuitry to sense data from or store data in a selected memory cell within a selected column of the columns **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z**. The column decoder **70**

is connected to the read/write buffer **55** to select which of the columns **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z** is to be activated for sensing or storing data. The column decoder **70** receives an address, which is decoded to provide the selection of the column **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z**. The read/write buffer **55** is connected to an input/output circuit **60**. The input/output circuit **60** contains a receiver to acquire data from the connector **65a**, **65b**, ..., **65m**, **65n**, ..., **65z** and a driver to transfer data to the connector **65a**, **65b**, ..., **65m**, **65n**, ..., **65z**. The connector **65a**, **65b**, ..., **65m**, **65n**, ..., **65z** is in communication with external circuitry for transfer of the data.

[0008] It is apparent to one skilled in the art that the number of columns **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z** associated with an input/output circuit **60** determines the efficiency of the redundancy of the array. This assumes that there is one redundant column **35** of memory cells **40a**, **40b**, ..., **40z** within each sub-array **15a**, **15b**, ..., **15z** and **20a**, ..., **20z**. In embedded memory applications, especially for SRAM applications, there may actually be a one-to-one correspondence of columns **25a**, ..., **25z** of memory cells **30a**, **30b**, ..., **30z** to the input/output circuits **60**.

[0009] Referring now to Fig. 2 for a description of a memory having a redundant column of memory cells associated with multiple memory arrays. In this illustration the memory is constructed of two arrays of memory cells **105** and **110**. Within the two memory arrays **105** and **110**, sub-arrays **115a**, **115b**, ..., **115z** and **120a**, ..., **120z** are composed of columns **125a**, ..., **125z** of memory cells **130a**,

130b, ..., 130z. A redundant column **135** of memory cells **140a, 140b, ..., 140z** is positioned to be associated with the memory arrays **5** and **10**. Each of the columns **125a, ..., 125z** of memory cells **130a, 130b, ..., 130z** is connected to one the redundancy implementation switches **145a, ..., 145z**. The redundant column **135** of memory cells **140a, 140b, ..., 140z** is connected to all the redundancy implementation switches **145a, ..., 145z**.

[0010] The redundancy implementation switches **145a, ..., 145z** are connected to the fuse box **150** which provides the necessary programming or indication of a fault within the columns **125a, ..., 125z** of memory cells **130a, 130b, ..., 130z** for all the sub-arrays **115a, 115b, ..., 115z** and **120a, ..., 120z**. If no fault occurs, the columns **125a, ..., 125z** of memory cells **130a, 130b, ..., 130z** are connected directly to the read/write buffer **155**. However, if a fault is detected during testing of the memory, the fuse box **150** is programmed to indicate the column **125a, ..., 125z** of memory cells **130a, 130b, ..., 130z** containing the fault. The programming of the fuse box **155** sets the redundancy implementation switch **145a, ..., 145z** associated with the faulty column **125a, ..., 125z** of memory cells **130a, 130b, ..., 130z** such that the redundant column **135** of memory cells **140a, 140b, ..., 140z** is now connected to the read/write buffer **155**.

[0011] The read/write buffer **155** contains the necessary circuitry to sense data from or store data to a selected memory cell within a selected column of the columns **125a, ..., 125z** of memory cells **130a, 130b, ..., 130z**. The column decoder **170** is connected to the read/write buffer **155** to select which of the

columns **125a, ..., 125z** of memory cells **130a, 130b, ..., 130z** is to be activated for sensing or storing of data. The column decoder **170** receives an address, which is decoded to provide the selection of the column **125a, ..., 125z** of memory cells **130a, 130b, ..., 130z**. The read/write buffer **155** is connected to an input/output circuit **160**. The input/output circuit **160** contains a receiver to acquire data from the connector **165a, 165b, ..., 165m, 165n, ..., 165z** and a driver to transfer data to the connector **165a, 165b, ..., 165m, 165n, ..., 165z**. The connector **165a, 165b, ..., 165m, 165n, ..., 165z** is in communication with external circuitry for transfer of the data.

[0012] It apparent to one skilled in the art that the number of columns **125a, ..., 125z** of memory cells **130a, 130b, ..., 130z** within the sub-arrays **115a, 115b, ..., 115z** and **120a, ..., 120z** and the total number of all the sub-arrays **115a, 115b, ..., 115z** and **120a, ..., 120z** determines the length of the connections to the redundant column **135** of memory cells **140a, 140b, ..., 140z**. The length of these connections has a detrimental impact on the performance of the memory when the redundant columns **135** of memory cells **140a, 140b, ..., 140z** are implemented.

[0013] U. S. Patent 5,742,556 (Tavrow, et al.) describes a redundancy scheme for semiconductor RAMS. This integrated circuit memory structure includes a plurality of regular columns of memory cells arranged in a sequence such that each regular column except the last one has an associated adjacent regular column. Each regular column has associated sense amplifier circuitry and read

write driver circuitry. The structure also includes a programmable element that responds to stimulus by providing a signal that identifies one of the regular columns as a defective column.

[0014] U. S. Patent 5,612,918 (McClure) describes redundancy architecture that reduces the complexity of the redundancy structure because it has fewer pass gates in the redundant decoder.

[0015] US Patent 5,257,229 (McClure, et al.) describes a column redundancy architecture for a read/write memory whereby an integrated circuit memory has its primary memory array arranged into blocks with redundant columns. Each of the redundant column decoders includes a set of fuses for storing the column address responsive to its associated redundant column.

[0016] U. S. Patent 5,134,584 (Boler, et al.) describes a configurable device that uses a plurality of parallel units that are made up of cells for storing individual bits of information. These cells are identified by address signals and selected to be interrogated. If a nonfunctional cell is detected within a parallel unit that parallel unit may be decoupled from the interrogator. The remainder of the parallel units is then shifted to different interrogators.

[0017] U. S. Patent 4,807,191 (Flannagan) describes redundancy for block-architecture memory. This is explained as two stacks of memory blocks. Each block of sense amplifiers is coupled to a memory block. Located at the bottom of each stack of memory blocks is a redundant block of columns of memory cells.

The redundant sense amplifier is also coupled to a redundant global data line. An input/output multiplexer is coupled to all of the global data lines. If one of the redundant columns replaces a defective column for a particular address, then the redundant global data line carries data which corresponds to the external data.

5 [0018] U. S. Patent 4,691,301 (Anderson) describes a semiconductor memory with redundant column circuitry that includes a row of shared predecoder and predecoders. The selected decode output is determined by the row shared predecoder. A switch bank of single pole-double throw switches selects between a normal and a redundant output. When a defective column is replaced, all of the
10 switches between the redundant column and the defective column have their states changed and the redundant column is activated. The address for each of the columns then has a lower position than the defective column incremented by one.

Summary of the Invention

15 [0019] An object of this invention is to provide a yield enhancement circuit that minimally impacts timing performance upon implementation of a redundant circuit within an integrated circuit.

[0020] Another object of this invention is to provide a yield enhancement circuit for replacing a defective circuit with a redundant circuit while having a small
20 effect in the area occupied by the integrated circuit.

[0021] To accomplish at least one these objects, a yield enhancement circuit is provided by substituting a redundant sub-circuit for a faulty sub-circuit in an integrated circuit such as memory. A memory is formed by an array of memory cells arranged in rows and columns. The redundant circuit is a redundant column memory cells or a redundant sub-circuit of the integrated circuit which is intended to replace a faulty column of memory cells within the memory array or integrated circuit.

[0022] The yield enhancement circuit has a plurality of fault indication devices. Each fault indication device is associated with one sub circuit of the integrated circuit such that one fault indication device is activated to generate a fault signal to express the existence of a fault within the faulty sub-circuit of the integrated circuit. Additionally each fault indication device that is associated with selected adjacent sub-circuits of the integrated circuit is activated generate the fault signal to express the existence of the fault within the faulty circuit of the integrated circuit.

[0023] The yield enhancement circuit has a fault detection device in communication with the plurality of fault indication devices to determine the existence of the faulty sub-circuit within the integrated circuit. The fault detection device transmits a redundancy implementation signal upon determination of existence of the faulty circuit.

[0024] The yield enhancement circuit further has a plurality of redundancy activation circuits that are in communication with the fault detection device in

order to receive the redundancy implementation signal. Each redundancy activation circuit is in communication with one of the fault indication devices.

Each redundancy activation circuit is associated with the sub-circuit to which the fault indication device is associated to selectively transfer input/output signals to a designated path dependent on the expression of the existence of a fault within the integrated circuit.

[0025] The redundancy activation circuit transfers the input/output signals of the circuit to their designated paths, if the fault indication device is not activated indicating that the associated sub-circuit has no fault and the redundancy implementation signal indicates that no fault exists in the integrated circuit. Further, the redundancy activation circuit transfers the input/output signals of the circuit to their designated path, if the fault indication device is not activated indicating that the associated circuit has no fault, but the redundancy implementation signal indicates that the fault exists in the integrated circuit. Whenever, the fault indication device is activated indicating existence of a faulty circuit and the redundancy implementation signal indicates that the fault exists in the integrated circuit, the input/output signals of the adjacent sub-circuit are transferred to the designated path.

[0026] The memory as above described is preferably a static random access memory, however dynamic random access memory, or non-volatile random access memory may be used with the yield enhancement circuit.

[0027] The columns of memory cells are connected to a read/write buffer connected to the column of memory cells to sense data stored in selected memory cells of the column and to store data to the memory cells of the column. The read/write buffer is connected to the designated path. The designated path is an input/output driver/receiver circuit that transfers the input/output signals from/to external circuitry.

[0028] Each fault indication device is comprised of a fuse. When the fuse is intact, the sub-circuit does not contain the fault and when the fuse is not intact, the sub-circuit contains the fault. Further, each fault indication device has a logical combining circuit. The logical combining circuit combines the fault signal indication device with the fault indication device that is associated with selected adjacent sub-circuits.

Brief Description of the Drawings

[0029] Fig. 1 is a diagram of a memory array illustrating yield enhancement employing redundant columns of the prior art.

[0030] Fig. 2 is a diagram of a memory array illustrating yield enhancement employing redundant columns of the prior art.

[0031] Fig. 3 is a diagram of a memory array illustrating yield enhancement employing redundant columns of this invention.

[0032] Fig. 4 is a schematic diagram of the multiplexer-Input/Output circuit of Fig. 3.

[0033] Fig. 5 s a diagram of the yield enhancement circuit of this invention.

Detailed Description of the Invention

5 [0034] The memory circuit of this invention is particularly suited (but not exclusively) to SRAM that is embedded with other circuitry in an integrated circuit. The memory circuit of this invention incorporates an architecture that permits a single redundant column of memory cells and minimizes the effects of the interconnection wiring of the redundant column on the performance of the
10 memory. The single redundant column of memory cells is placed relatively central to the placement of the arrays of memory cells for which the redundant column is to provide yield enhancement protection.

[0035] A fault indication device is associated with each column of the arrays of memory cells. Generally, the fault indication device has a fuse that is destroyed
15 if the associated column of memory cells has a fault. This causes a fault signal that is transmitted to selected adjacent fault indication devices. The fault indication device has a combinational logic circuit such as an OR gate that combines the fault signal of the fault indication device with the selected fault indication devices transmitting their fault signals to the current fault signal device.
20 This structure permits the locating of the column of memory cells having the fault.

[0036] A fault detection device collects the results of the logical combination of all the fault signals to determine that a redundancy should be implemented. The fault detection device activate activates a redundancy implementation signal indicating that redundancy is to be applied. Further the redundancy implementation signal is structured to indicate which array has the fault in instances of multiple arrays that are protected by one redundant column of memory cells.

[0037] Each column of memory cells has its own read/write buffer to sense data from or store data in selected cells in the column of memory cells. The input and output ports of the read/write buffer is connected respectively to the output of a first multiplexer and the primary input of a second multiplexer. The primary input of the second multiplexer is connected to the output of the read/write circuit of an adjacent column of memory cells. An input/output circuit is associated with each column of memory cells. The input from external circuits as received by the input/output circuit is transferred to the primary input of the first multiplexer and to the secondary input of the first multiplexer of an adjacent column of memory cells.

[0038] Each column of memory cells has an associated multiplex control circuit connected to the first and second multiplexers of the associated column of memory cells. The fault signal of the associated fault indication device and the redundancy implementation signal are applied to the multiplex control circuit to determine whether the associated column of memory cells is used or the

adjacent column of memory cells is used to sense or store data for the associated input/output circuit.

[0039] The column of the memory array for which the redundant column of memory cells provides protection is nearest to the redundant column of memory cells and is connected such that the redundant column of memory cells is adjacent to the column of memory cells. The redundant column of memory cells has its own read/write buffer to sense data from and store data to the redundant column of memory cells once redundancy is implemented. The output of the read/write buffer associated with the redundant column of memory cells is connected to each of the second inputs of the second multiplexers of each of the columns of memory to which the redundant column of memory cells is adjacent. The read/write buffer is connected to receive the output of a redundancy multiplexer whose inputs are connected to the input/output circuits of the adjacent columns of memory cells.

[0040] When there is no fault in any of the columns of memory cells none of the fuse are destroyed and the fault signal and the redundancy implementation signals are not activated. The first and second multiplexers are set such that the data signals from the input/output circuit are transferred to the associated column of memory cells. However, if there is a fault in a column of memory cells, the fuse associated with the faulty column of memory cells is destroyed and the fault signal is activated. The fault signal for all the fault indication devices for the columns of memory cells placed between the faulty column of memory cells and

the redundant column of memory cells is also activated. The redundancy implementation signal is activated indicating which of the arrays contains the fault.

[0041] For columns of memory cells not between the faulty column of memory cells and the redundant column of memory cells and the columns of memory cells in other memory arrays, the fault signal is not activated. The first and second multiplexers of these columns receive the redundancy implementation signal and the inactive fault signal. The multiplexers associated with these columns transfer the data signals from the input/output circuits are transferred between their associated columns of memory cells.

[0042] For those columns having their fault signals activated and the redundancy implementation signal activated, the multiplexer for those columns transfer the data signals from the input/output circuit to the adjacent column. The last column of the array with the faulty column of memory cells is now the redundant column of memory cells.

[0043] Refer now to Figs. 3, 4, and 5 for a more detailed discussion of the integrated circuit memory with a yield enhancement circuit of this invention. In this illustration, the memory is constructed of two arrays of memory cells **205** and **210**. Within the two memory arrays **205** and **210**, sub-arrays **215a**, **215b**, ..., **215z** and **220a**, ..., **220z** are composed of columns **225a**, ..., **225z** of memory cells **230a**, **230b**, ..., **230z**. A redundant column **235** of memory cells **240a**, **240b**, ..., **240z** is positioned to be associated with the memory arrays **205** and

210. Each of the columns **225a, ..., 225z** of memory cells **230a, 230b, ..., 230z** is connected to one read/write buffer circuit **255a, ..., 255z**. The redundant column **235** of memory cells **240a, 240b, ..., 240z** is connected to its own read/write buffer **275**.

5 [0044] The sub-arrays **215a, 215b, ..., 215z** and **220a, ..., 220z** are shown as having multiple columns with an associated read/write buffer circuit **255a, ..., 255z**. The column decoder **270** decodes a column address signal to select which of the columns **225a, ..., 225z** of memory cells **230a, 230b, ..., 230z** is to be connected to the read/write buffer circuit **255a, ..., 255z**. Alternately, the
10 read/write buffer circuit **255a, ..., 255m, 255n, ... 255z** has sufficient circuitry to have individual read/write buffer circuits for each column **225a, ..., 225z** of memory cells **230a, 230b, ..., 230z**. The structure of the yield enhancement circuit of this invention is described as if there were single columns **225a, ..., 225z** of memory cells **230a, 230b, ..., 230z** associated with a read/write buffer
15 circuit **255a, ..., 255z**. It would be apparent to one skilled in the necessary changes to have multiple columns **225a, ..., 225z** of memory cells **230a, 230b, ..., 230z** associated with the read/write buffer circuit **255a, ..., 255m, 255n, ... 255z**.

[0045] In the prior art, the read write buffer circuits are connected to be in direct
20 communication with the associated input/output circuit. In the memory integrated circuit of this invention, the input and output ports of each of the read/write buffer circuits **255a, ..., 255m, 255n, ... 255z** is connected respectively to the

multiplexer-Input/Output circuit **450a**, ..., **450z**. Referring to Fig. 4, each of the
 the input ports **455a**, ..., **455z** of each of the read/write buffer circuits **255a**, ...,
255m, **255n**, ... **255z** of Fig. 3 is connected to an output **455** of an associated
 first multiplexer **300**. Each of output ports **453a**, ..., **453z** of each of the
 5 read/write buffer circuits **255a**, ..., **255m**, **255n**, ... **255z** of Fig. 3 is connected to
 the primary input **453** of a second multiplexer **295**. The secondary input **451** of
 the second multiplexer **295** is connected to the output ports **453a**, ..., **453z** of
 each of the read/write buffer circuits **255a**, ..., **255m**, **255n**, ... **255z** of an
 adjacent column **225a**, ..., **225z** of memory cells **230a**, **230b**, ..., **230z** or an
 10 adjacent sub-array **215a**, **215b**, ..., **215z** and **220a**, ..., **220z** of Fig. 3. An
 input/output circuit **260** is associated with each sub-array **215a**, **215b**, ..., **215z**
 and **220a**, ..., **220z** of Fig. 3. The input **265** from external circuits as received by
 the input/output circuit **260** is transferred to the primary input of the first
 multiplexer **300** and as an output **459** of the multiplexer-Input/Output circuit **450a**,
 15 ..., **450z** to the secondary input **457** of the first multiplexer **300** of a multiplexer-
 Input/Output circuit **450a**, ..., **450z** associated with an adjacent column **225a**, ...,
225z of memory cells **230a**, **230b**, ..., **230z** as shown in Fig. 3.

[0046] Each multiplexer-Input/Output circuit **450a**, ..., **450z** has a multiplex
 control circuit **285** connected to the first multiplexers **300** and second multiplexer
 20 **295**. The mutiplex control circuit **285** receives a redundancy implementation
 signal (**REDUN**) **415** and the redundancy implementation signal (**iohit x**) **410**.
 Referring back to Fig. 3, the fault signal of an associated fault indication device
250a, ..., **250m**, **250n**, ... **250z** generates a redundancy implementation signal

(**iohit x**) **410** that is applied to the multiplex control circuit **285** to generate the multiplex control signals (**n ihit x**) **430** of Fig. 4 that determine whether the associated column of memory cells within sub-arrays **215a**, **215b**, ..., **215z** and **220a**, ..., **220z** is used or the adjacent column of memory cells within the sub-arrays **215a**, **215b**, ..., **215z** and **220a**, ..., **220z** is used to sense or store data transferred by the associated input/output circuit **260a**, ..., **260m**, **260n**, ... **260z**.

[0047] The fault indication devices **250a**, ..., **250m**, **250n**, ... **250z**, as shown in Fig. 5, have a fuse **252** that is connected between the ground reference point and the resistor **254**. The resistor **254** is connected between the power voltage source **V_{DD}** and the fuse **252**. The junction of the fuse **252** and the resistor **254** is the terminal (**iohitnx**) **405** that provides the fault signal. If there is no fault in an associated column **225a**, ..., **225z** of memory cells **230a**, **230b**, ..., **230z** of the sub-arrays **215a**, **215b**, ..., **215z** and **220a**, ..., **220z**, the fuse is intact and the fault signal is at an inactive state (0). Alternately, if there is a fault in an associated column **225a**, ..., **225z** of memory cells **230a**, **230b**, ..., **230z** of the sub-arrays **215a**, **215b**, ..., **215z** and **220a**, ..., **220z**, the fuse is destroyed and the fault signal is at an active state (1). Each of the fault indication devices **250a**, ..., **250m**, **250n**, ... **250z** further has a logical combining circuit **256** which combines the fault signal **405a**, ..., **405m**, **405n**, ... **405z** of the present fault indication device **250a**, ..., **250m**, **250n**, ... **250z** with the combined fault signal **410a**, ..., **410m**, **410n**, ... **410z** of an adjacent fault indication device **250a**, ..., **250m**, **250n**, ... **250z** that is in the direction opposite the redundant column **235** of memory cells **240a**, **240b**, ..., **240z**.

[0048] The logical combination of the fault signals **410m** and **410n** from each array **205** and **210** is applied to the fault detection circuit **280**. The fault detection circuit **280** combines the logical combination of fault signals **410m** and **410n** to create the redundancy implementation signals **415a** and **415b**. The fault
5 detection circuit **280** is connected to the multiplex control circuits **285** to transfer the redundancy implementation signal **415a** to the multiplexer control circuit **285a**, ..., **285m** for the left array **205** and the redundancy implementation signal **415b** to the multiplex control circuit **285n**, ... **285z** for the right array **210**.

[0049] The read/write buffer **275** is connected to the multiplexer **305** that receives
10 the input data signals from the adjacent input/output circuits **260m** and **260n** of the left array **205** and the right array **210**. The multiplexer **305** is connected to the multiplex control circuit **290** to receive the a redundancy signal **420** indicating the existence of a fault within one of the memory arrays **205** and **210** and the array selection switch signal **425** indicating which array **205** and **210** has the
15 fault. The fault detection circuit **280** is connected to the multiplex control circuit **290** associated with the redundant column **235** of memory cells **240a**, **240b**, ..., **240z** to provide the redundancy implementation signals **415a** and **415b**.

[0050] If there are no faults in the memory arrays **205** and **210**, the multiplex control circuits **285a**, ..., **285m**, **285n**, ... **285z** for the first multiplexers **300** and
20 second multiplexers **295** are set such that the data signals are directly transferred between the sub-arrays **215a**, **215b**, ..., **215z** and **220a**, ..., **220z** and their associated input/output circuits **260**. However, if for instance, a column of

the sub-array 1 **215b** has a fault, the fuse **252** within the fault indication circuit **250b** is destroyed to activate the fault signal **405b**. The logic combination circuit **256** provides a logical ORing of the fault signals from the fuse **252** and the adjacent fault indication circuit **250a** that is opposite the fault indication circuit **250b** from the redundant column **235** of memory cells **240a**, **240b**, ..., **240z**. The ORing of the fault signal activates a combined fault signal **410b**. The successive fault indication signals combine the combined fault signal **410b**, ..., **410m** to generate the input **410m** to the fault detection circuit **280**. The left redundancy implementation signal **415a** is activated and the right redundancy implementation signal **415b** remains inactive, thus indicating that the fault exists in the left memory **205**.

[0051] The multiplex control circuit **285a** receives an inactive combined fault signal **410a** and an active redundancy implementation signal **415a**. The multiplex control circuit **285a** sets the multiplex control signal (**neihit a**) **430a** such that the first multiplexer **300a** and the second multiplexer **295a** transfer the data signals from the input/output circuit **260a** to its associated sub-array **215a**. The combined fault signals **410b**, ..., **410m** and the redundancy implementation signal **415a** are the inputs to the multiplex control circuit **285a**, ..., **285m** for the left array **205**. In the illustration being described, these signals are active causing the multiplex control circuits **285b**, ..., **285m** to set the multiplex control signals (**neihit x**) **430b**, ..., **430m** to cause the first multiplexers **300b**, ..., **300m** and second multiplexers **295b**, ..., **295m** to transfer the data signals from the input/output circuits **260b**, ..., **260m** to and from the adjacent columns of the sub-

arrays **215b**, ..., **215z**. The multiplexers **295m** and **305** are set to transfer the data signals between the input/output circuit **260m** and the redundant column **235** of memory cells **240a**, **240b**, ..., **240z**.

[0052] The redundancy implementation signal **415b** and the combined fault
5 signals **410n**, ..., **410z** are not activated. The data signals from the input/output circuit **260n**, ..., **260z** are transferred between their associated columns of the sub-arrays **220a**, ..., **220z**.

[0053] In summary, the circuit as described in Figs. 3, 4 and 5 performs a method
for yield enhancement of an integrated circuit by substituting a redundant circuit
10 for a faulty circuit of the integrated circuit. The circuit provides a fault indication associated with each sub-circuit of the integrated circuit such that one fault indication is activated to generate a fault signal to express existence of a fault within the faulty circuit of the integrated circuit. Additionally, each fault indication associated with selected adjacent sub-circuits of the integrated circuit activates
15 the fault signal to express the existence of the fault within the faulty circuit of the integrated circuit. The circuit then determines the existence of the faulty circuit within the integrated circuit from the fault signal. A redundancy implementation signal is generated upon determination of the existence of the faulty circuit.
Redundancy is activated upon generating the redundancy implementation signal
20 and one of the fault indications associated with the sub-circuit to selectively transfer input/output signals of the sub-circuit associated with the fault indication

and an adjacent sub-circuit to a designated path dependent on the expression of the existence of a fault within the integrated circuit.

[0054] If the fault indication is not activated, thus indicating that the associated sub-circuit has no fault and the redundancy implementation signal indicates that no fault exists in the integrated circuit, the input/output signals of the circuit are transferred to their designated path. If the fault indication is not activated indicating that the associated sub-circuit has no fault, but the redundancy implementation signal indicates that the fault exists in the integrated circuit, the input/output signals of the circuit are transferred to their designated path. However, if the fault indication is activated indicating existence of a faulty circuit and the redundancy implementation signal indicates that the fault exists in said integrated circuit, the input/output signals of said adjacent sub-circuit are transferred to the designated path.

[0055] While this invention has been particularly shown and described with reference to the preferred embodiments thereof, it will be understood by those skilled in the art that various changes in form and details may be made without departing from the spirit and scope of the invention.

[0056] The invention claimed is: